

GaAs MMIC Digital Attenuator Chip, DC-20GHz

Performance characteristics

Frequency range: DC-20GHz

Insertion loss: 1.6 dB typ

Attenuation range: 0~20dB

Bit Count: 1 digit

50Ohm input/output

Chip size: 1.25 x 1.12 x 0.1mm

Product Introduction

GDA-0020-1C-20-PD is a GaAs MMIC 1-bit Digital attenuator chip, with a frequency range of DC-20GHz, insertion loss of 1.6dB, attenuation range of 0-20dB, switching speed of 20ns. The integrated logic of the chip adopts -5V power supply and 0/+5V control. The chip through-hole metallization process ensures good grounding, and the back is metallized, suitable for eutectic sintering or conductive adhesive bonding processes. This CNC attenuator can operate up to 40GHz.

Usage restriction parameter¹

| | | | |
|----------------------------|--------------|--|--|
| Control voltage range | -0.5V～+6V | | |
| Power supply voltage range | -6V | | |
| Maximum input power | +27dBm | | |
| working temperature | -55 ~ +85°C | | |
| Storage temperature | -65 ~ +150°C | | |

【1】 Exceeding any of the above maximum limits may result in permanent damage.

Electrical parameter(Ta=+25° C, VEE=-5V, VC=0/+5V)


| Index | Minimum value | Typical value | Maximum value | Unit |
|--|---------------|---------------|---------------|--------|
| Frequency range | | DC~20 | | GHz |
| Insertion loss | - | 1.6 | - | dB |
| Attenuation range | | 0~20 | | dB |
| Attenuation number | | 1 | | bite |
| Attenuation step | | 20 | | dB |
| Attenuation accuracy (all frequency bands) | | -0.5 ~ -0.3 | | dB |
| Phase fluctuation (full frequency band) | | -0.3 ~ +0.5 | | degree |
| Input return loss | - | 18 | - | dB |
| Output Return Loss | - | 18 | - | dB |

| | | | | |
|----------------------|---|----|----|-----|
| Switching speed | - | 20 | - | ns |
| P-1dB | - | 23 | - | dBm |
| Power supply voltage | - | -5 | - | V |
| Control voltage | 0 | - | +5 | V |
| Current | - | 2 | - | mA |


GaAs MMIC Digital Attenuator Chip, DC-20GHz

Main indicator testing curve


Insertion loss vs. Frequency




Reference attenuation state vs. Frequency



Input echo vs. Frequency





Output echo vs. Frequency




Attenuation additional phase shift vs. Frequency

Attenuation accuracy vs. Frequency



GaAs MMIC Digital Attenuator Chip, DC-20GHz

External structure²



[2]The units in the figure are all micrometers.

Definition of bonding pressure point

| Bond point number | Functional symbols | Function Description |
|-------------------|--------------------|---|
| 1 | RF1 | The signal end is connected to a 50 ohm circuit externally, and there is no integrated DC isolation capacitor inside the chip |
| 2 | RF2 | The signal end is connected to a 50 ohm circuit externally, and there is no integrated DC isolation capacitor inside the chip |
| 3 | VEE | Power supply end |
| 4 | VC | Attenuation control pads, refer to the truth table for attenuation control |
| Chip bottom | GND | The bottom of the chip needs to have sufficient and good contact with RF and DC ground |

Truth table

| Supply voltage | Control input | Attenuation state |
|----------------|---------------|--|
| VEE | IN | / |
| -5V | 0V | Initial state N=0: attenuation amount is 0 |
| -5V | +5V | Attenuation state N=1: Attenuation amount is 20dB |

Suggested assembly diagram

