

GaAs MMIC5-bit CNC Attenuator Chip, 0.01-18GHz

Performance characteristics

Frequency range: 0.01-18GHz
 Insertion loss: 2.6dB typ
 Attenuation range: 0.5~15.5dB
 Bit count: 5
 Attenuation step: 0.5dB
 Power supply voltage: -5V power supply
 Control voltage: 0/+5V control
 50Ohm input/output
 Chip size: QFN 4X4

Product Introduction

GDA-0018-5B-PD-CQ5 is a GaAs MMIC 5-bit CNC attenuator chip, with a frequency range of 0.01-18GHz, insertion loss of 2.6dB, switching speed of 50ns, integrated driver inside the chip, and 0/+5V control. This CNC attenuator adopts a 4X4mm surface mount lead-free ceramic tube shell, which can achieve airtight packaging. The surface of the pin pads is treated with gold plating technology, suitable for reflow soldering installation process.

Use restriction parameters

Power supply voltage range	-6V
Control voltage range	-0.5V~+5.5V
Maximum input power	+27dBm
Working temperature	-55 ~ +85°C
Storage temperature	-65 ~ +150°C

Exceeding any of the above maximum limits may result in permanent damage.

Electrical parameters (Ta=+25 ° C, VEE=-5V, 0/+5V control)


Index	Minimum value	Typical value	Maximum value	Unit
Frequency range	0.01-18			GHz
Insertion loss	-	2.6	-	dB
Attenuation range	0.5~15.5			dB
Attenuation step	0.5			dB
Attenuation number	5			bite
Attenuation accuracy (fundamental state)	-	-	±0.7	dB
Attenuation accuracy (fundamental state) (RMS)	-	0.4	-	dB
Additional phase shift	-	-	7.0	degree

(fundamental state)				
Additional phase shift (fundamental state) (RMS)	-	1	-	degree
Input return loss	-	15	-	dB
Output Return Loss	-	15	-	dB
Switching speed	-	50	-	ns
P-1dB	-	22	-	dBm
Supply voltage		-5	-	V
Power supply current		6	-	mA


GaAs MMIC5-bit CNC Attenuator Chip, 0.01-18GHz

Main indicator testing curve


Insertion loss vs. frequency




Reference attenuation state vs. frequency



Input Echo vs. Frequency





Output Echo vs. Frequency




Attenuation accuracy (fundamental state) vs. frequency

Additional phase shift (fundamental state) vs. frequency




GaAs MMIC5-bit CNC Attenuator Chip, 0.01-18GHz


External structure



vertical view



Top view



Side view

The units in the figure are all millimeters, with an unspecified tolerance of $\pm 0.15\text{mm}$


Truth table

Truth table						
VC1	VC2	VC3	VC4	VC5	VEE	Conduction pathway
0V	0V	0V	0V	0V	-5V	Initial state N=0: attenuation amount is 0
+5V	0V	0V	0V	0V		Attenuation state N=1: Attenuation amount is 0.5
0V	+5V	0V	0V	0V		Attenuation state N=2: Attenuation amount is 1
0V	0V	+5V	0V	0V		Attenuation state N=4: Attenuation amount is 2
0V	0V	0V	+5V	0V		Attenuation state N=8: Attenuation amount is 4
0V	0V	0V	0V	+5V		Attenuation state N=16: Attenuation amount is 8
0V	0V	0V	0V	0V		

GaAs MMIC5-bit CNC Attenuator Chip, 0.01-18GHz

Solder joint serial number	Functional symbols	Function Description
3	RFIN	The RF signal input terminal is externally connected to a 50 ohm circuit, and there is no integrated DC isolation capacitor inside the chip
16	RFOUT	The RF signal output terminal is externally connected to a 50 ohm circuit, and there is no integrated DC isolation capacitor inside the chip
7	VEE	Power on port, requires an external 100pF capacitor
8、9、10、11、12	VC	Attenuation control pads, see truth table for attenuation control details
2、4、15、17	GND	The pins need to be well grounded with RF and DC
Chip bottom	GND	The bottom of the chip needs to be well grounded with RF and DC
other	NC	No welding required

Recommended circuit



Precautions for use

- Sealing material: Ceramic material that meets ROHS specifications
- Lead frame material: copper alloy
- Lead surface coating: gold, with a gold layer thickness greater than 0.3um MIN
- Maximum reflow soldering peak temperature: 260 °C